






**AC SYNCHRONOUS MOTOR
MOTOR-16.5T**



No	Rated Voltage (VAC)	Rated Frequency (Hz)	Rated Speed (R.P.M)	Power Consumption (W)	Current Consumption (mA)	Input Torque (kgf.cm)
TY-50B	100	50/60	10/12	<=4	<=40	>=1.5
TY-50A	220~240	50/60	10/12	<=4	<=20	>=1.5
TY-50B	100	50/60	4/5	<=4	<=40	>=3
TY-50A	220~240	50/60	4/5	<=4	<=20	>=3
TY-50B	100	50/60	2.5/3	<=4	<=40	>=6
TY-50A	220~240	50/60	2.5/3	<=4	<=20	>=6
Insulation Class	Starting Voltage (V)	Temperature Rise (K)	Noise (dB)	Dielectric Strength (V/S)	Direction	
A.F	<=93	<=65	<=40	1800	Cw ccw cw/ccw	
A.F	<=187	<=65	<=40	1800	Cw ccw cw/ccw	
A.F	<=93	<=65	<=40	1800	Cw ccw cw/ccw	
A.F	<=187	<=65	<=40	1800	Cw ccw cw/ccw	
A.F	<=93	<=65	<=40	1800	Cw ccw cw/ccw	
A.F	<=187	<=65	<=40	1800	Cw ccw cw/ccw	

Email: sales@peterparts.com • Phone: 585-265-2000 • Fax: 585-265-2542