

Ni-Mh Battery High Rate Discharge Series

| Size | P/N | Nominal Voltage | Nominal Capacity (mAh) | Standard Charge | | Rapid Charge | | Dimensions With Tube | | Weight (g) |
|------|---------------------------------|-----------------|------------------------|-----------------|------------|--------------|------------|----------------------|------------|------------|
| | | | | Current (mA) | Time (hrs) | Current (mA) | Time (hrs) | Diameter (mm) | Height(mm) | |
| AA | HYMP-AA600P | 1.2 | 600 | 60 | 16 | 600 | 1.2 | 14.0 | 48.5 | 16.0 |
| AA | HYMP-AA700P | 1.2 | 700 | 70 | 16 | 700 | 1.2 | 14.0 | 48.5 | 16.0 |
| AA | HYMP-AA800P | 1.2 | 800 | 80 | 16 | 800 | 1.2 | 14.0 | 48.5 | 17.0 |
| AA | HYMP-AA900P | 1.2 | 900 | 90 | 16 | 900 | 1.2 | 14.0 | 48.5 | 17.0 |
| AA | HYMP-AA1000P | 1.2 | 1000 | 100 | 16 | 1000 | 1.2 | 14.0 | 48.5 | 18.0 |
| AA | HYMP-AA1100P | 1.2 | 1100 | 110 | 16 | 110 | 1.2 | 14.0 | 48.5 | 20.0 |
| AA | HYMP-AA1200P | 1.2 | 1200 | 120 | 16 | 1200 | 1.2 | 14.0 | 48.5 | 22.0 |
| AA | HYMP-AA1300P | 1.2 | 1300 | 130 | 16 | 1300 | 1.2 | 14.0 | 48.5 | 24.0 |
| SC | HYMP-4/5SC1400P | 1.2 | 1400 | 140 | 16 | 1400 | 1.2 | 22.5 | 33.5 | 45.0 |
| SC | HYMP-4/5SC1200P | 1.2 | 1200 | 120 | 16 | 1200 | 1.2 | 22.5 | 33.5 | 43.0 |
| SC | HYMP-SC1300P | 1.2 | 1300 | 130 | 16 | 1300 | 1.2 | 22.5 | 42.5 | 48.0 |
| SC | HYMP-4/5SC1600P | 1.2 | 1600 | 160 | 16 | 1600 | 1.2 | 22.5 | 33.5 | 46.0 |
| SC | HYMP-SC1500P | 1.2 | 1500 | 150 | 16 | 1500 | 1.2 | 22.5 | 42.5 | 52.0 |
| SC | HYMP-SC1800P | 1.2 | 1800 | 180 | 16 | 1800 | 1.2 | 22.5 | 42.5 | 58.0 |
| SC | HYMP-SC2000P | 1.2 | 2000 | 200 | 16 | 2000 | 1.2 | 22.5 | 42.5 | 62.0 |
| SC | HYMP-SC2200P | 1.2 | 2200 | 220 | 16 | 2200 | 3.5 | 22.5 | 42.5 | 53.0 |
| SC | HYMP-SC2500P | 1.2 | 2500 | 250 | 16 | 2500 | 3.5 | 22.5 | 42.5 | 55.0 |
| SC | HYMP-SC2800P | 1.2 | 2800 | 280 | 16 | 2800 | 1.2 | 22.5 | 42.5 | 57.0 |
| SC | HYMP-SC3000P | 1.2 | 3000 | 300 | 16 | 3000 | 3.5 | 22.5 | 42.5 | 60.0 |
| C | HYMP-C3000P | 1.2 | 3000 | 300 | 16 | 3000 | 1.2 | 22.5 | 48.5 | 75.0 |
| D | HYMP-D5000P | 1.2 | 5000 | 500 | 16 | 5000 | 7.5 | 32.5 | 59.5 | 135.0 |
| D | HYMP-D6000P | 1.2 | 6000 | 600 | 16 | 1200 | 7.5 | 32.5 | 59.5 | 140.0 |
| F | HYMP-F7000P | 1.2 | 7000 | 700 | 15 | 1400 | 7.5 | 32.5 | 89.5 | 220.0 |
| F | HYMP-F8000P | 1.2 | 8000 | 800 | 16 | 4000 | 7.5 | 32.5 | 89.5 | 220.0 |

For More Detailed Information

Please Contact Us At Peter Parts Electronics, Inc.

Phone 585-265-2000, Fax 585-265-2542 or <mailto:sales@peterparts.com>